

# 2-Channel Audioamp S 3000 / S 1300

Modern electronics, classical design and excellent audio qualities are combined in the SEEBURG power amplifiers to provide a reliable work horse equally suited to installations and mobile systems.

A 2 stage switching mode power supply ensures low weight and high efficiency. The highly effective copper heat sink cooling system and easily accessible high capacity air filters provide for easy and minimal maintenance.



## PRODUCT SPECIFICATIONS

	S 3000	S 1300
<b>Description</b>	2-Channel Audioamp	2-Channel Audioamp
<b>Power EIA</b>	2 x 1150 Watt / 4 Ω	2 x 550 Watt / 4 Ω
both channels driven (0.1% THD, 20 Hz - 20 kHz)	2 x 800 Watt / 8 Ω	2 x 350 Watt / 8 Ω
<b>Power EIA</b> bridge mode	2300 Watt / 8 Ω	1.100 Watt / 8 Ω
<b>Peak Output Voltage</b> bridge mode	400 V	250 V
<b>Signal to noise ratio</b>	100 dp	100 db
<b>Channel separation</b> @ 1000 Hz	60 dp	60 dp
<b>Input Impedance</b>	20 k	20 k
<b>Slew Rate</b>	45 Volts / us	45 Volts / us
<b>Damping Factor</b>	1000	500
<b>Gain</b>	26 dp / 32 dB / 1.4 V	26 dp / 32 dB / 1.4 V
<b>Cooling</b>	3 x fans, front to rear airflow, temperature controlled speed	
<b>Mode Switch</b>	stereo / mono / bridge	
<b>Indicators</b>	Power / Bridge / 8 x Gain / Limit / Protect	
<b>Inputs</b>	XLR in/loop thru	
<b>Outputs</b>	Speakon A: 1+/-A, 2+/-B, Speakon B: 1+/-B	
<b>Mains Connector</b>	220-230 V / 50-60 Hz, Neutrik Power Con	
<b>Weight</b>	11,4 kg	10 kg
<b>Size</b> height x width x depth	88 (2 HE) x 483 (19") x 453 / 413 mm	
<b>Order No.</b>	<b>01822</b>	<b>01820</b>

